

Wall Mounted Touch Panel

Scanstrip BATTERY PANEL

Art.nr. 71154-01/15

ANETA

PROFESSIONAL

4 Zone/1-5 color/Glass touch panel/Color slide/Wireless remote 30m distance/AAA x 2 battery



BATTERY PANEL
4 Zone RGB+CCT

CE RoHS LVD RED

Features

- Touch panel 4 zone 1-5 color RF remote.
- Each zone can remote control multiple Scanstrip CTR 2.4G LED controllers.
- Ultra sensitive high strength glass touch panel with touch color slide in the middle.
- Smooth and accurate color adjustment by touching the color slide.
- Touch keys with chord tones and LED indicator.
- Free installation, no wiring, removable.
- AAA x 2 battery powered.
- White & Black glass panel available.


Technical Parameters

Input and Output	
Output signal	RF(2.4GHz)
Working voltage	3VDC AAA x 2)
Working current	< 5mA
Standby current	< 20μA
Standby time	1 year
Remote distance	30m
Environment	
Operation temperature	Ta:-30 °C~+55 °C
Case temperature(Max.)	Tc: +65 °C
IP rating	IP20

Safety and EMC	
EMC standard (EMC)	ETSI EN 301 489-1 V2.2.3 ETSI EN 301 489-17 V3.2.4
Safety standard(LVD)	EN 62368-1:2020+A11:2020
Radio Equipment(RED)	ETSI EN 300 328 V2.2.2
Certification	CE,EMC,LVD,RED
Warranty	
Warranty	5 years
Weight	
Net weight	156 g
Gross weight	192 g


Scanstrip BATTERY PANEL - Wall Mounted Touch Panel

Mechanical Structures and Installations



Installation diagram:

Typical base as below:



To fix the panel, two options are offered for selection:

Option 1: fix it on the wall with two screws.

Option 2: adhere it to the wall using glue

Match Remote Control (two match ways)

End user can choose the suitable match/delete ways. Two options are offered for selection:

Use the controller's Match key

Match:

Short press match key, immediately press zone key of the touch panel.

The LED indicator fast flash a few times means match is successful.

Delete:

Press and hold match key for 5s to delete all match.

The LED indicator fast flash a few times means all matched remotes were deleted.

Use Power Restart

Match:


Switch off the power of the receiver, then switch on power, repeat again.
Immediately short press zone key 3 times on the touch panel.
The light blinks 3 times means match is successful.

Delete:

Switch off the power of the receiver, then switch on power, repeat again.
Immediately short press zone key 5 times on the touch panel.
The light blinks 5 times means all matched remotes were deleted.

Key function

Scanstrip BATTERY PANEL



Note: After touch power key to turn off light, long press power key for 5 seconds will turn on or turn off tone.

Safety information

1. Read all instructions carefully before you begin this installation.
2. When installing battery, pay attention to the battery positive and negative polarity.
A long time without the remote control, remove the battery.
When remote distance becomes smaller and insensitive, replace the battery.
3. If no response from the receiver, please re-match the remote.
4. Gently handle remote, beware of falling.
5. For indoor and dry location use only.