

Select your language

- German
- English
- Spanish
- French
- Dutch
- Italian
- Polish
- Czech
- Russian
- Norwegian Bokmål

Worldwide English



NZMH2-PX100-TZ - NZM2 PXR25 circuit breaker - integrated energy measurement class 1, 100A, 3p, Screw terminal, earth-fault protection and zone selectivity



192157 NZMH2-PX100-TZ

[Overview](#) [Specifications](#) [Resources](#)



192157 NZMH2-PX100-TZ

NZM2 PXR25 circuit breaker - integrated energy measurement class 1, 100A, 3p, Screw terminal, earth-fault protection and zone selectivity

EL-Nummer (Norway)

4362749

The xEffect NZM...PX...-TZ circuit breaker range with power expert release (PXR) electronic triggering system covers use cases for full range protection including earth fault protection with only four compact sizes and is suitable for the IEC market. The integrated energy measuring function supplies currents, voltages and active energy (kWh) with accuracy class 1 according to IEC 61557-12. Zone selectivity for extended protection included. Test function and settings via micro USB port directly on the switch. Modular function groups always make mounting flexible and may be supplemented by the comprehensive range of accessories. R.m.s. value measurement and thermal memory.



- [Delivery program](#)

- [Technical data](#)

- [Design verification as per IEC/EN 61439](#)

- [Technical data ETIM 7.0](#)

- [Characteristics](#)

- [Dimensions](#)

Delivery program

Product range
Circuit-breaker
Protective function
Systems, cable, selectivity and generator protection
Earth-fault protection
Zone selectivity
Standard/Approval
IEC
Installation type
Fixed
Release system
Electronic release
Construction size
NZM2

Description

LSIG overload protection and delayed and non-delayed short-circuit protective device, earth-fault protection
Class 1 energy measurement, r.m.s. value measurement, and "thermal memory"
USB interface for configuration and test function with Power Xpert Protection Manager software
Zone selectivity ZSI
Interface module in equipment supplied.
Optionally communication-capable with internal Modbus RTU module or CAM
Number of poles

3 pole

Standard equipment

Screw connection

Switching capacity

400/415 V 50 Hz [I_{cu}]


150 kA

Rated current = rated uninterrupted current [$I_n = I_u$]

Rated current = rated uninterrupted current [$I_n = I_u$]

100 A

Setting range

Overload trip  [I_t]

40 - 100 A

Short-circuit releases  [I_{tm}] Non-delayed  [$I_t = I_n \times \dots$]

2 - 18

Short-circuit releases  [I_{tm}] Delayed  [$I_{sd} = I_t \times \dots$]

2 - 10

Setting range of earth fault release min. [$I_g = I_n \times \dots$]

20

Setting range of earth fault release max. [$I_g = I_n \times \dots$]

100

Technical data

General

Standards

IEC/EN 60947

Protection against direct contact

Finger and back of hand proof to VDE 0106 Part 100

Climatic proofing

Damp heat, constant, to IEC 60068-2-78

Damp heat, cyclic, to IEC 60068-2-30

Ambient temperature Ambient temperature, storage

- 40 - + 70 °C

Ambient temperature Operation

-25 - +70 °C

Mechanical shock resistance (10 ms half-sinusoidal shock) according to IEC 60068-2-27

20 (half-sinusoidal shock 20 ms) g


Safe isolation to EN 61140 Between auxiliary contacts and main contacts

500 V AC

Safe isolation to EN 61140 between the auxiliary contacts

300 V AC

Mounting position

Vertical and 90° in all directions	
	With XFI earth-fault release:
	- NZM1, N1, NZM2, N2: vertical and 90° in all directions
	with plug-in unit
	- NZM1, N1, NZM2, N2: vertical, 90° right/left
	with withdrawable unit:
	- NZM3, N3: vertical, 90° right/left
- NZM4, N4: vertical	
with remote operator:	
- NZM2, N(S)2, NZM3, N(S)3, NZM4, N(S)4: vertical and 90° in all directions	

Direction of incoming supply

as required

Degree of protection Device

In the operating controls area: IP20 (basic degree of protection)

Degree of protection Enclosures

With insulating surround: IP40

With door coupling rotary handle: IP66

Degree of protection Terminations

Tunnel terminal: IP10

Phase isolator and strip terminal: IP00

Other technical data (sheet catalogue)

[Weight](#)

[Temperature dependency, Derating](#)

[Effective power loss](#)

Circuit-breakers

Rated current = rated uninterrupted current [$I_n = I_u$]

100 A

Rated surge voltage invariability [U_{imp}] Main contacts

8000 V

Rated surge voltage invariability [U_{imp}] Auxiliary contacts

6000 V

Rated operational voltage [U_e]

690 V AC

Overvoltage category/pollution degree

III/3

Rated insulation voltage [U_i]

690 V

Use in unearthed supply systems

690 V

Switching capacity

Rated short-circuit making capacity [I_{cm}] 240 V [I_{cm}]

330 kA

Rated short-circuit making capacity [I_{cm}] 400/415 V [I_{cm}]

330 kA

Rated short-circuit making capacity [I_{cm}] 440 V 50/60 Hz [I_{cm}]

286 kA

Rated short-circuit making capacity [I_{cm}] 525 V 50/60 Hz [I_{cm}]

110 kA

Rated short-circuit making capacity [I_{cm}] 690 V 50/60 Hz [I_{cm}]

40 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cu} to IEC/EN 60947 test cycle O-t-OO [I_{cu}] 240 V 50/60 Hz [I_{cu}]

150 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cu} to IEC/EN 60947 test cycle O-t-OO [I_{cu}] 400/415 V 50/60 Hz [I_{cu}]

150 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cu} to IEC/EN 60947 test cycle O-t-OO [I_{cu}] 440 V 50/60 Hz [I_{cu}]

130 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cu} to IEC/EN 60947 test cycle O-t-OO [I_{cu}] 525 V 50/60 Hz [I_{cu}]

50 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cu} to IEC/EN 60947 test cycle O-t-OO [I_{cu}] 690 V 50/60 Hz [I_{cu}]

20 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cs} to IEC/EN 60947 test cycle O-t-OO-t-OO [I_{cs}] 240 V 50/60 Hz [I_{cs}]

150 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cs} to IEC/EN 60947 test cycle O-t-OO-t-OO [I_{cs}] 400/415 V 50/60 Hz [I_{cs}]

150 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cs} to IEC/EN 60947 test cycle O-t-OO-t-OO [I_{cs}] 440 V 50/60 Hz [I_{cs}]

130 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cs} to IEC/EN 60947 test cycle O-t-OO-t-OO [I_{cs}] 525 V 50/60 Hz [I_{cs}]

37.5 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}] I_{cs} to IEC/EN 60947 test cycle O-t-OO-t-OO [I_{cs}] 690 V 50/60 Hz [I_{cs}]

5 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}]

Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit-breaker.

Rated short-time withstand current $t = 0.3$ s [I_{cw}]

1.9 kA

Rated short-time withstand current $t = 1$ s [I_{cw}]

1.9 kA

Utilization category to IEC/EN 60947-2

A

Lifespan, mechanical (of which max. 50 % trip by shunt/undervoltage release) [Operations]

20000

Lifespan, electrical AC-1400 V 50/60 Hz [Operations]

10000

Lifespan, electrical AC-1415 V 50/60 Hz [Operations]

10000

Lifespan, electrical AC-1690 V 50/60 Hz [Operations]

7500

Lifespan, electrical Max. operating frequency

120 Ops/h

Total break time at short-circuit

< 10 ms

Terminal capacity

Standard equipment

Screw connection

Optional accessories

Box terminal

Tunnel terminal

connection on rear

Round copper conductor Box terminal Solid

1 x (10 - 16)

2 x (6 - 16) mm²

Round copper conductor Box terminal Stranded

1 x (25 - 185)

2 x (25 - 70) mm²

Round copper conductor Tunnel terminal Solid

1 x 16 mm²

Round copper conductor Tunnel terminal Stranded 1-hole

1 x (25 - 185) mm²

Round copper conductor Bolt terminal and rear-side connection Direct on the switch Solid

1 x (10 - 16)

2 x (6 - 16) mm²

Round copper conductor Bolt terminal and rear-side connection Direct on the switch Stranded

1 x (25 - 185)

2 x (25 - 70) mm²

Al circular conductor Tunnel terminal Solid

1 x 16 mm²

Al circular conductor Tunnel terminal Stranded Stranded

1 x (25 - 185) mm²

Cu strip (number of segments x width x segment thickness) Box terminal [min.]

2 x 9 x 0.8 mm

Cu strip (number of segments x width x segment thickness) Box terminal [max.]

10 x 16 x 0.8

(2x) 8 x 15.5 x 0.8 mm

Cu strip (number of segments x width x segment thickness) Bolt terminal and rear-side connection Flat copper strip, with holes [min.]

2 x 16 x 0.8 mm

Cu strip (number of segments x width x segment thickness) Bolt terminal and rear-side connection Flat copper strip, with holes [max.]

10 x 24 x 0.8 mm

Copper busbar (width x thickness) [mm] Bolt terminal and rear-side connection Screw connection

MB

Copper busbar (width x thickness) [mm] Bolt terminal and rear-side connection Direct on the switch [min.]

16 x 5 mm

Copper busbar (width x thickness) [mm] Bolt terminal and rear-side connection Direct on the switch [max.]

24 x 8 mm

Control cables

1 x (0.75 - 2.5)

2 x (0.75 - 1.5) mm²

Design verification as per IEC/EN 61439

Technical data for design verification

Rated operational current for specified heat dissipation [I_n]

100 A

Equipment heat dissipation, current-dependent [P_{vid}]

8.25 W

Operating ambient temperature min.

-25 °C

Operating ambient temperature max.

+70 °C

IEC/EN 61439 design verification

10.2 Strength of materials and parts 10.2.2 Corrosion resistance

Meets the product standard's requirements.

10.2 Strength of materials and parts 10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

10.2 Strength of materials and parts 10.2.3.2 Verification of resistance of insulating materials to normal heat
Meets the product standard's requirements.

10.2 Strength of materials and parts 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects
Meets the product standard's requirements.

10.2 Strength of materials and parts 10.2.4 Resistance to ultra-violet (UV) radiation
Meets the product standard's requirements.

10.2 Strength of materials and parts 10.2.5 Lifting
Does not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts 10.2.6 Mechanical impact
Does not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts 10.2.7 Inscriptions
Meets the product standard's requirements.

10.3 Degree of protection of ASSEMBLIES
Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances
Meets the product standard's requirements.

10.5 Protection against electric shock
Does not apply, since the entire switchgear needs to be evaluated.

10.6 Incorporation of switching devices and components
Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections
Is the panel builder's responsibility.

10.8 Connections for external conductors
Is the panel builder's responsibility.

10.9 Insulation properties 10.9.2 Power-frequency electric strength
Is the panel builder's responsibility.

10.9 Insulation properties 10.9.3 Impulse withstand voltage
Is the panel builder's responsibility.

10.9 Insulation properties 10.9.4 Testing of enclosures made of insulating material
Is the panel builder's responsibility.

10.10 Temperature rise
The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating
Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility
Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function
The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss10.0.1-27-37-04-09 [AJZ716013])

Rated permanent current I_n

100 A

Rated voltage

690 - 690 V

Rated short-circuit breaking capacity I_{cu} at 400 V, 50 Hz

150 kA

Overload release current setting

40 - 100 A

Adjustment range short-term delayed short-circuit release

2 - 10 A

Adjustment range undelayed short-circuit release

2 - 18 A

Integrated earth fault protection

Yes

Type of electrical connection of main circuit

Screw connection

Device construction

Built-in device fixed built-in technique

Suitable for DIN rail (top hat rail) mounting


No

DIN rail (top hat rail) mounting optional


Yes
Number of auxiliary contacts as normally closed contact
0
Number of auxiliary contacts as normally open contact
0
Number of auxiliary contacts as change-over contact
0
With switched-off indicator
No
With under voltage release
No
Number of poles
3
Position of connection for main current circuit
Front side
Type of control element
Rocker lever
Complete device with protection unit
Yes
Motor drive integrated
No
Motor drive optional
Yes
Degree of protection (IP)
IP20

Characteristics

Characteristic curve



Let-through current
Characteristic curve



Let-through energy

Dimensions

- Blow out area, minimum clearance to adjacent parts
- Minimum clearance to adjacent parts

CAD data

- [Product-specific CAD data](#)
(Web)
- [3D Preview](#)
(Web)

DWG files

- [DA-CD-nzm2_3p](#)
File
(Web)

Step files

- [DA-CS-nzm2_3p](#)
File
(Web)

Additional product information

- [Weight](#)
(Web)
- [Temperature dependency, Derating](#)
(Web)
- [Effective power loss](#)
(Web)
- [additional technical information for NZM power switch](#)
(PDF)



Product photo

- 
[sg04718_c](#)
Photo
- 
[sg04718_l](#)
Photo
- 
[sg04718_r](#)
Photo

Dimensions single product

- [123X312](#)
Line drawing
Circuit-breaker, switch-disconnector, 3-pole
 - Blow out area, minimum clearance to adjacent parts
 - Minimum clearance to adjacent parts
- [123X341](#)
Line drawing
Circuit-breakers, switch-disconnectors

Characteristic curve

- 
[1230DIA-178](#)
Coordinate visualization
- 
[1230DIA-185](#)
Coordinate visualization

Instruction Leaflet

- [IL012099ZU](#)

Asset
(PDF, Language independent)

Download-Center

- [Download-Center \(this item\)](#)
Eaton EMEA Download-Center - download data for this item
- [Download-Center](#)
Eaton EMEA Download-Center



[Generate data sheet in PDF format](#)



[Generate data sheet in Excel format](#)



[Write a comment](#)

[Imprint](#) [Privacy Policy](#) [Legal Disclaimer](#) [Terms and Conditions](#)

© 2021 by Eaton Industries GmbH

