

# Eaton 265722

Catalog Number: 265722

Eaton Moeller series NZM - Molded Case Circuit Breaker. Circuit-breaker, 3p, 100A, N1-M100



Photo is representative

## General specifications

<b>Product Name</b>	<b>Catalog Number</b>
Eaton Moeller series NZM molded case circuit breaker thermo-magnetic	265722
	<b>Model Code</b>
	NZMN1-M100
<b>EAN</b>	<b>Product Length/Depth</b>
4015082657222	88 mm
<b>Product Height</b>	<b>Product Width</b>
145 mm	90 mm
<b>Product Weight</b>	<b>Compliances</b>
1.011 kg	RoHS conform
<b>Certifications</b>	
IEC/EN 60947	
IEC	

## Type

Circuit breaker

## Special features

Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity  $I_{cn}$ )  
 Rated current = rated uninterrupted current: 100 A  
 Terminal capacity hint: Up to 95 mm<sup>2</sup> can be connected depending on the cable manufacturer.

With phase-failure sensitivity  
 Tripping class 10 A  
 IEC/EN 60947-4-1, IEC/EN 60947-2

The circuit-breaker fulfills all requirements for AC-3 switching category.

## Application

Use in unearthed supply systems at 690 V

## Amperage Rating

100 A

## Voltage rating

690 V - 690 V

## Circuit breaker frame type

NZM1

### 10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

### 10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

### 10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the

## Brochures

[eaton-feerum-the-whole-grain-solution-success-story-en-us.pdf](#)

[eaton-digital-nzm-brochure-br013003en-en-us.pdf](#)

## Catalogs

[eaton-digital-nzm-catalog-ca013003en-en-us.pdf](#)

## Certification reports

[DA-DC-03\\_N1](#)

## Characteristic curve

[eaton-circuit-breaker-nzm-mccb-characteristic-curve.eps](#)

[eaton-circuit-breaker-nzm-mccb-characteristic-curve-058.eps](#)

[eaton-circuit-breaker-let-through-current-nzm-mccb-characteristic-curve-002.eps](#)

## Drawings

[eaton-circuit-breaker-nzm-mccb-dimensions-017.eps](#)

[eaton-circuit-breaker-switch-nzm-mccb-dimensions-014.eps](#)

[eaton-general-ie-ready-dilm-contactor-standards.eps](#)

## eCAD model

[ETN.NZMN1-M100](#)

[ETN.265722.edz](#)

## Installation videos

[Introduction of the new digital circuit breaker NZM](#)

[The new digital NZM Range](#)

## mCAD model

[DA-CS-nzm1\\_3p](#)

[DA-CD-nzm1\\_3p](#)

## Technical data sheets

[eaton-nzm-technical-information-sheet](#)

## Wiring diagrams

[eaton-manual-motor-starters-starter-nzm-mccb-wiring-diagram.eps](#)

[eaton-manual-motor-starters-starter-msc-r-reversing-starter-wiring-diagram.eps](#)

switchgear must be observed.

#### 10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

#### 10.2.2 Corrosion resistance

Meets the product standard's requirements.

##### 10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

##### 10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

##### 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

#### 10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

#### 10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.2.7 Inscriptions

Meets the product standard's requirements.

#### 10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.4 Clearances and creepage distances

Meets the product standard's requirements.

#### 10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

#### 10.8 Connections for external conductors

Is the panel builder's responsibility.

#### 10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

#### 10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

#### 10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

#### Fitted with:

Thermal protection

#### Pollution degree

3

#### Mounting Method

Built-in device fixed built-in technique

Fixed

#### Climatic proofing

Damp heat, cyclic, to IEC 60068-2-30

Damp heat, constant, to IEC 60068-2-78

#### Equipment heat dissipation, current-dependent

23.85 W

#### Utilization category

A (IEC/EN 60947-2)

#### Isolation

300 V AC (between the auxiliary contacts)

500 V AC (between auxiliary contacts and main contacts)

#### Ambient operating temperature - max

70 °C

#### Ambient operating temperature - min

-25 °C

#### Ambient storage temperature - max

70 °C

#### Ambient storage temperature - min

40 °C

#### Protection against direct contact

Finger and back-of-hand proof to VDE 0106 part 100

#### Rated insulation voltage (Ui)

690 V

#### Rated operating power at AC-3, 230 V

30 kW

Rated operating power at AC-3, 400 V

55 kW

Switch off technique

Thermomagnetic

Degree of protection

IP20 (basic degree of protection, in the operating controls area)

IP20

Direction of incoming supply

As required

Electrical connection type of main circuit

Other

Lifespan, mechanical

20000 operations

Overvoltage category

III

Rated operational current

99 A (400 V AC-3)

Degree of protection (IP), front side

IP40 (with insulating surround)

IP66 (with door coupling rotary handle)

Degree of protection (terminations)

IP10 (tunnel terminal)

IP00 (terminations, phase isolator and strip terminal)

Number of poles

Three-pole

Terminal capacity (copper strip)

Min. 2 segments of 9 mm x 0.8 mm at box terminal

Max. 9 segments of 9 mm x 0.8 mm at box terminal

Lifespan, electrical

7500 operations at 415 V AC-3

7500 operations at 690 V AC-1

10000 operations at 415 V AC-1

5000 operations at 690 V AC-3

10000 operations at 400 V AC-1

7500 operations at 400 V AC-3

Functions

Phase failure sensitive

Motor protection

Shock resistance

20 g (half-sinusoidal shock 20 ms)

Rated operational current for specified heat dissipation ( $I_n$ )

100 A

Short-circuit release non-delayed setting - max

1250 A

Short-circuit release non-delayed setting - min

800 A

Handle type

Rocker lever

Instantaneous current setting ( $I_i$ ) - max

1250 A

Instantaneous current setting ( $I_i$ ) - min

800 A

Number of operations per hour - max

120

Overload current setting ( $I_r$ ) - max

100 A

Overload current setting ( $I_r$ ) - min

80 A

Rated short-circuit breaking capacity  $I_{cs}$  (IEC/EN 60947) at 230 V, 50/60 Hz

85 kA

Rated short-circuit breaking capacity  $I_{cs}$  (IEC/EN 60947) at 400/415 V, 50/60 Hz

35 kA

Rated short-circuit breaking capacity  $I_{cs}$  (IEC/EN 60947) at 440 V, 50/60 Hz

35 kA

Rated short-circuit breaking capacity  $I_{cs}$  (IEC/EN 60947) at 525 V, 50/60 Hz

10 kA

Rated short-circuit breaking capacity  $I_{cs}$  (IEC/EN 60947) at 690 V, 50/60 Hz

7.5 kA

Standard terminals

Box terminal

Optional terminals

Connection on rear. Screw terminal. Tunnel terminal

Release system

Thermomagnetic release

#### Short-circuit total breaktime

< 10 ms

#### Terminal capacity (aluminum solid conductor/cable)

10 mm<sup>2</sup> - 16 mm<sup>2</sup> (2x) direct at switch rear-side connection

10 mm<sup>2</sup> - 16 mm<sup>2</sup> (1x) direct at switch rear-side connection

16 mm<sup>2</sup> (1x) at tunnel terminal

#### Terminal capacity (aluminum stranded conductor/cable)

25 mm<sup>2</sup> - 35 mm<sup>2</sup> (2x) direct at switch rear-side connection

25 mm<sup>2</sup> - 35 mm<sup>2</sup> (1x) direct at switch rear-side connection

25 mm<sup>2</sup> - 95 mm<sup>2</sup> (1x) at tunnel terminal

#### Terminal capacity (control cable)

0.75 mm<sup>2</sup> - 1.5 mm<sup>2</sup> (2x)

0.75 mm<sup>2</sup> - 2.5 mm<sup>2</sup> (1x)

#### Terminal capacity (copper busbar)

Max. 16 mm x 5 mm direct at switch rear-side connection

M6 at rear-side screw connection

Min. 12 mm x 5 mm direct at switch rear-side connection

#### Terminal capacity (copper solid conductor/cable)

6 mm<sup>2</sup> - 16 mm<sup>2</sup> (2x) direct at switch rear-side connection

16 mm<sup>2</sup> (1x) at tunnel terminal

6 mm<sup>2</sup> - 16 mm<sup>2</sup> (2x) at box terminal

10 mm<sup>2</sup> - 16 mm<sup>2</sup> (1x) at box terminal

10 mm<sup>2</sup> - 16 mm<sup>2</sup> (1x) direct at switch rear-side connection

#### Terminal capacity (copper stranded conductor/cable)

10 mm<sup>2</sup> - 70 mm<sup>2</sup> (1x) at box terminal

10 mm<sup>2</sup> - 70 mm<sup>2</sup> (1x) direct at switch rear-side connection

25 mm<sup>2</sup> (2x) direct at switch rear-side connection

6 mm<sup>2</sup> - 25 mm<sup>2</sup> (2x) at box terminal

25 mm<sup>2</sup> - 95 mm<sup>2</sup> (1x) at 1-hole tunnel terminal

#### Rated short-circuit breaking capacity I<sub>cu</sub> (IEC/EN 60947) at 400/415 V, 50/60 Hz

35 kA

#### Rated short-circuit making capacity I<sub>cm</sub> at 400/415 V, 50/60 Hz

105 kA

#### Rated short-circuit making capacity I<sub>cm</sub> at 440 V, 50/60 Hz

74 kA

#### Rated short-circuit making capacity I<sub>cm</sub> at 525 V, 50/60 Hz

40 kA

#### Rated short-circuit making capacity I<sub>cm</sub> at 690 V, 50/60 Hz

17 kA

#### Rated short-circuit making capacity I<sub>cm</sub> at 240 V, 50/60 Hz

187 kA

Rated impulse withstand voltage (Uimp) at auxiliary contacts

6000 V

Rated impulse withstand voltage (Uimp) at main contacts

6000 V

Power loss

23.9 W



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)