

[United States](#) [Select your location](#)

[Sign in](#)

We make what matters work*

[Products](#) [Digital Services](#) [Markets](#) [Support](#) [Company](#)

Search

[Products](#)

- [Actuators and motion control](#)
- [Backup power, UPS, surge & IT power distribution](#)
- [Clutches and brakes](#)
- [Conduit, cable & wire management](#)
- [Cylinders](#)
- [Differentials](#)
- [Ducting solutions](#)
- [Electrical circuit protection](#)
- [Electric vehicles and EV charging](#)
- [Electronic components](#)

- [Enclosures](#)
- [Energy storage systems](#)
- [Engine solutions](#)
- [Filtration solutions](#)
- [Fuel systems, emissions and components](#)
- [Furniture](#)
- [Golf grips](#)
- [Hose, tubing, fittings and connectors](#)
- [Hydraulic motors and generators](#)

- [Hydraulic power packs and accumulators](#)
- [Industrial controls, drives, automation and sensors](#)
- [Life support systems](#)
- [Lighting and controls](#)
- [Low-voltage power distribution & control systems](#)
- [Medium-voltage power distribution & control systems](#)
- [Plastics](#)
- [Process safety, automation, test and measurement](#)
- [Pumps](#)

- [Residential](#)
- [Safety, security & emergency communications](#)
- [Server racks, enclosures & airflow management](#)
- [Support systems](#)
- [Transmissions](#)
- [Utility & grid solutions](#)
- [Valves](#)
- [Wiring devices & connectivity](#)

[Digital](#)

- [Brightlayer Experience Hub](#)
- [Explore our digital catalog](#)
- [Discover Brightlayer](#)
- [Understanding Industry 4.0](#)

- [For developers](#)

[Services](#)

Close Search

[Markets](#)

Close Search

- [Aerospace](#)
- [Buildings](#)
- [Data centers](#)
- [Eaton Experience Centers](#)
- [Food and beverage](#)
- [Government and military](#)
- [Healthcare](#)
- [Machine building](#)

- [Marine](#)
- [Mining, metals and minerals](#)
- [Oil and gas](#)
- [Rail](#)
- [Renewables](#)
- [Residential](#)
- [Utilities](#)

- [Vehicles](#)

[Support](#)

Close Search

- [Contact technical support](#)
- [Download center](#)
- [How to buy](#)
- [Terms and conditions](#)
- [Tools](#)
- [Training and education](#)
- [Warranty and returns](#)

[Company](#)

Close Search

- [Overview](#)
- [About us](#)
- [News & insights](#)
- [Careers](#)
- [Investor relations](#)
- [Research & development](#)

- [Corporate governance](#)
- [Sustainability](#)
- [Inclusion & diversity](#)
- [Ethics & compliance](#)
- [Partnering with Eaton](#)

- [Selling to Eaton](#)

[MyEaton](#)

Close Search

Quick links



Eaton Moeller® series PKZM01 Motor-protective circuit-breaker
278476

[Overview](#) [Specifications](#) [Resources](#)

How to buy

[Back to search](#)

[Download](#) [Zoom](#)

Photo is representative

[Download](#) [Zoom](#)

Photo is representative

[Download](#) [Zoom](#)





Photo is representative

[Download](#) [Zoom](#)

Photo is representative

[Previous](#) [Next](#)

[Download](#) [Zoom](#)

- 
- 
- 
- 

[Previous](#) [Next](#)

278476

Eaton Moeller® series PKZM01 Motor-protective circuit-breaker, 660 V 690 V: 0.12 kW, $I_r= 0.16 - 0.25$ A, IP20 PKZM01-0,25

[Add a free sample to the cart](#)

×



Products cannot be sold together

Products in your cart cannot be sold together in one transaction. Please choose to either keep your existing cart, or create a new cart with this product.

You can purchase your products in separate transactions.

[Keep My Cart](#)

[Create a New Cart](#)

×



Item is already in the cart.

[Okay](#)



Photo is representative

Designed to work together

Discover other Eaton products and accessories built to enhance this product.

- [082882](#)

082882
Eaton Moeller® series NHI Standard auxiliary contact, NHI-E, 1 N/O, 1 NC, Can be fitted to the front, Screw terminals
- [072896](#)

072896
Eaton Moeller® series NHI Standard auxiliary contact, 1 N/O, 1 NC, Can be retrofitted on the right side of motor-protective circuit-breakers, Screw terminals
- [032720](#)

032720
Eaton Moeller® series PKZ Extension terminal, 3p, 25mm² BK25/3-PKZ0
- [072894](#)

072894
Eaton Moeller® series NHI Standard auxiliary contact, 2N/O+1N/C, screw connection
- [101452](#)

101452
Eaton Moeller® series BBA Busbar adapter, 45 mm, 32 A, DIN rail: 2 BBA0-32
- [073138](#)

073138
Eaton Moeller® series U-PKZ0 Undervoltage release PKZ0(4), PKE, AC, 400 V 50 Hz, Screw terminals
- [073135](#)

073135
Eaton Moeller® series U-PKZ0 Undervoltage release PKZ0(4), PKE, AC, 230 V 50 Hz, Screw terminals
- [101451](#)

101451
Eaton Moeller® series BBA Busbar adapter, 45 mm, 25 A, DIN rail: 1 BBA0-25
- [063961](#)

063961
Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 2, 90 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary contacts or voltage releases

- [082884](#)

082884

Eaton Moeller® series NHI Standard auxiliary contact, NHI-E, 1 N/O, Can be fitted to the front, Screw terminals

- [063960](#)

063960

Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 4, 180 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary contacts or voltage releases

- [232289](#)

232289

Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 3, 135 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary contacts or voltage releases

- [281404](#)

281404

Eaton Moeller® series CI Insulated enclosure, IP65_x, +operating membrane, for PKZ01

- [232290](#)

232290

Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 5, 225 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary contacts or voltage releases

- [101481](#)

101481

Eaton Moeller® series BBA Busbar adapter, 45 mm, 25 A, DIN rail: 2

- [262518](#)

262518

Eaton Moeller® series PKZ Extension terminal, 3p, 25mm² BK25/3-PKZ0-E

- [082881](#)

082881

Eaton Moeller® series PKZ0 Current limiter, 3p, 63A, 400VAC/100kA, 690VAC/10kA

- [072898](#)

072898

Eaton Moeller® series PKZ Trip indicator, 2 x 1 N/O, Screw terminals

- [044945](#)

044945

Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 2, 99 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary

contacts or voltage releases

- [229681](#)

229681

Eaton Moeller® series NHI Standard auxiliary contact, 1N/O, flush mounting, spring clamp connection

[Go to Previous Item](#)

[Go to Next Item](#)

- [082882](#)

082882

Eaton Moeller® series NHI Standard auxiliary contact, NHI-E, 1 N/O, 1 NC, Can be fitted to the front, Screw terminals

- [072896](#)

072896

Eaton Moeller® series NHI Standard auxiliary contact, 1 N/O, 1 NC, Can be retrofitted on the right side of motor-protective circuit-breakers, Screw terminals

- [032720](#)

032720

Eaton Moeller® series PKZ Extension terminal, 3p, 25mm² BK25/3-PKZ0

- [072894](#)

072894

Eaton Moeller® series NHI Standard auxiliary contact, 2N/O+1N/C, screw connection

- [101452](#)

101452

Eaton Moeller® series BBA Busbar adapter, 45 mm, 32 A, DIN rail: 2 BBA0-32

- [073138](#)

073138

Eaton Moeller® series U-PKZ0 Undervoltage release PKZ0(4), PKE, AC, 400 V 50 Hz, Screw terminals

- [073135](#)

073135

Eaton Moeller® series U-PKZ0 Undervoltage release PKZ0(4), PKE, AC, 230 V 50 Hz, Screw terminals

- [101451](#)

101451

Eaton Moeller® series BBA Busbar adapter, 45 mm, 25 A, DIN rail: 1 BBA0-25

- [063961](#)

063961

Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 2, 90 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary contacts or voltage releases

- [082884](#)

082884

Eaton Moeller® series NHI Standard auxiliary contact, NHI-E, 1 N/O, Can be fitted to the front, Screw terminals

- [063960](#)

063960

Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 4, 180 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary contacts or voltage releases

- [232289](#)

232289

Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 3, 135 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary contacts or voltage releases

- [281404](#)

281404

Eaton Moeller® series CI Insulated enclosure, IP65_x, +operating membrane, for PKZ01

- [232290](#)

232290

Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 5, 225 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary contacts or voltage releases

- [101481](#)

101481

Eaton Moeller® series BBA Busbar adapter, 45 mm, 25 A, DIN rail: 2

- [262518](#)

262518

Eaton Moeller® series PKZ Extension terminal, 3p, 25mm² BK25/3-PKZ0-E

- [082881](#)

082881

Eaton Moeller® series PKZ0 Current limiter, 3p, 63A, 400VAC/100kA, 690VAC/10kA

- [072898](#)

072898

Eaton Moeller® series PKZ Trip indicator, 2 x 1 N/O, Screw terminals

- [044945](#)

044945

Eaton Moeller® series B3 Three-phase busbar link, Circuit-breaker: 2, 99 mm, For PKZM0-... or PKE12, PKE32 without side mounted auxiliary contacts or voltage releases

- [229681](#)

229681

Eaton Moeller® series NHI Standard auxiliary contact, 1N/O, flush mounting, spring clamp connection

[View more](#) [View less](#)

- [General specifications](#)
- [Product specifications](#)

General specifications

Product Name

Eaton Moeller® series PKZM01 Motor-protective circuit-breaker

Catalog Number

278476

Model Code

PKZM01-0,25

EAN

4015082784768

Product Length/Depth

93 mm

Product Height

90 mm

Product Width

45 mm

Product Weight

0.252 kg

Certifications

IEC/EN 60947

UL Category Control No.: NLRV

VDE 0660

UL File No.: E36332

CE

CSA

CSA Class No.: 3211-05

CSA-C22.2 No. 60947-4-1-14

IEC/EN 60947-4-1

UL

CSA File No.: 165628

UL 60947-4-1

Product specifications

Rated operational current for specified heat dissipation (In)

0.25 A

Terminal capacity (flexible with ferrule)

2 x (1 - 6) mm², ferrule to DIN 46228

1 x (1 - 6) mm², ferrule to DIN 46228

10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

Ambient operating temperature (enclosed) - min

25 °C

Rated operational power at AC-3, 380/400 V, 50 Hz

0.06 kW

10.4 Clearances and creepage distances

Meets the product standard's requirements.

10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

Switching capacity

0.25 A (3 contacts in series), DC-5 up to 250V

0.25 A, AC-3 up to 440 V

Stripping length (main cable)

10 mm

Ambient operating temperature (enclosed) - max

40 °C

Rated short-circuit breaking capacity Icu at 400 V AC

50 kA

10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

Ambient storage temperature - min

40 °C

Adjustment range undelayed short-circuit release - max

3.9 A

10.8 Connections for external conductors

Is the panel builder's responsibility.

Protection

Finger and back-of-hand proof, Protection against direct contact when actuated from front (EN 50274)

Actuator type

Push button

Rated operational power at AC-3, 440 V, 50 Hz

0.06 kW

Ambient operating temperature - max

55 °C

Rated operational power at AC-3, 220/230 V, 50 Hz

0 kW

Climatic proofing

Damp heat, constant, to IEC 60068-2-78

Damp heat, cyclic, to IEC 60068-2-30

Device construction

Built-in device fixed built-in technique

Features

Phase-failure sensitivity (according to IEC/EN 60947-4-1, VDE 0660 Part 102)

Lifespan, electrical

50,000 operations (at 400V, AC-3)

Static heat dissipation, non-current-dependent Pvs

0 W

Electrical connection type of main circuit

Screw connection

10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

Number of poles

Three-pole

Ambient operating temperature - min

-25 °C

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

Mounting position

Can be snapped on to IEC/EN 60715 top-hat rail with 7.5 or 15 mm height.

Rated uninterrupted current (Iu)

0.25 A

Short-circuit release

± 20% tolerance, Trip blocks

3.9 A, I_{rn}, Setting range max.

Basic device fixed 15.5 x I_u, Trip Blocks

10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

Heat dissipation per pole, current-dependent P_{vid}

1.72 W

Operating frequency

25 Operations/h

Product category

Motor protective circuit breaker

Short-circuit current rating (group protection)

50 kA, 600 V High Fault, Fuse, SCCR (UL/CSA)

600 A, 600 V High Fault, max. CB, SCCR (UL/CSA)

600 A, 600 V High Fault, max. Fuse, SCCR (UL/CSA)

50 kA, 600 V High Fault, CB, SCCR (UL/CSA)

Overload release current setting - min

0.16 A

Equipment heat dissipation, current-dependent P_{vid}

5.15 W

Heat dissipation capacity P_{diss}

0 W

Rated operational current (I_e)

0.25 A

Suitable for

Also motors with efficiency class IE3

Branch circuit: Manual type E if used with terminal, or suitable for group installations, (UL/CSA)

Internal resistance

26500 mΩ

Temperature compensation

≤ 0.25 %/K, residual error for T > 40°

-5 - 40 °C to IEC/EN 60947, VDE 0660

-25 - 55 °C, Operating range

Terminal capacity (solid)

1 x (1 - 6) mm²

2 x (1 - 6) mm²

Rated frequency - min

50 Hz

Short-circuit current

60 kA DC, up to 250 V DC, Main conducting paths

Power loss

5.15 W

10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

Lifespan, mechanical

50,000 Operations (Main conducting paths)

Terminal capacity (solid/stranded AWG)

18 - 10

Overload release current setting - max

0.25 A

10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

Overvoltage category

III

Degree of protection

Terminals: IP00

IP20

Rated frequency - max

60 Hz

Switch off technique

Thermomagnetic

Ambient storage temperature - max

80 °C

Adjustment range undelayed short-circuit release - min

3.9 A

Pollution degree

3

10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

Rated impulse withstand voltage (U_{imp})

6000 V AC

Connection

Screw terminals

10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

Functions

Motor protection

Phase failure sensitive

Rated operational voltage (U_e) - min

690 V

10.2.2 Corrosion resistance

Meets the product standard's requirements.

10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

10.2.7 Inscriptions

Meets the product standard's requirements.

Shock resistance

25 g, Mechanical, according to IEC/EN 60068-2-27, Half-sinusoidal shock 10 ms

Rated operational voltage (U_e) - max

690 V

Altitude

Max. 2000 m

Serial Number Verified :

Authenticated: ✓

The product is verified as being authentic; however, this does not guarantee the condition or fit for purpose of the product.

Brochures

- [Save time and space thanks to the new link module PKZM0-XDM32ME](#)
- [Motor Starters in System xStart - brochure](#)

Download all files

Catalogs

- [Switching and protecting motors - catalog](#)
- [Product Range Catalog Switching and protecting motors](#)

Characteristic curve

- [eaton-manual-motor-starters-characteristic-characteristic-curve-008.eps](#)
- [eaton-manual-motor-starters-characteristic-characteristic-curve-002.eps](#)
- [eaton-manual-motor-starters-characteristic-characteristic-curve-009.eps](#)

Download all files

Declarations of conformity

- [DA-DC-00004914.pdf](#)
- [DA-DC-00004884.pdf](#)

Drawings

- [eaton-manual-motor-starters-circuit-breaker-pkzm01-dimensions.eps](#)
- [eaton-general-ie-ready-dilm-contactor-standards.eps](#)
- [eaton-manual-motor-starters-circuit-breaker-pkzm01-3d-drawing-002.eps](#)
- [eaton-manual-motor-starters-mounting-3d-drawing-002.eps](#)

Download all files

eCAD model

- [ETN.PKZM01-0.25](#)

Installation instructions

- [IL122012ZU](#)
- [IL03407011Z](#)
- [IL03402034Z](#)

Download all files

Installation videos

- [WIN-WIN with push-in technology](#)

Manuals and user guides

- [IL122023ZU](#)

mCAD model

- [DA-CS-pkzm01](#)
- [DA-CD-pkzm01](#)

Download all files

[Export product specification](#)

-

x



Enter your city, state, or zip code or [Locate me](#)

City, state

Search

Show locations that offer:

- Product pickup
- Order online and ship product

- 278476

Eaton is an intelligent power management company dedicated to improving the quality of life and protecting the environment for people everywhere. We are guided by our commitment to do business right, to operate sustainably and to help our customers manage power — today and well into the future. By capitalizing on the global growth trends of electrification and digitalization, we're accelerating the planet's transition to renewable energy and helping to solve the world's most urgent power management challenges.

Company

- [About us](#)
- [Careers](#)
- [Inclusion and Diversity](#)
- [Investor relations](#)
- [Sustainability](#)
- [News and insights](#)
- [Slavery and human trafficking statement](#)

Quick links

- [Sign in](#)
- [Support](#)
- [Policies and statements](#)
- [Terms and conditions](#)
- [Responsible sourcing of conflict minerals](#)
- [Subscribe to emails](#)

Let's talk big ideas

-
-
-
-

[View all social media](#)

- [Sitemap](#)
- [Privacy, cookies & data protection policy](#)
- [Do not sell my data request \(CCPA and other states\)](#)

© 2023 Eaton. All Rights Reserved.

[Back to top of the page](#)

Are you sure?

[Cancel](#) [Sign out](#)

Are you sure?

[Cancel](#) [Sign out](#)

×

×