#### DATASHEET - INX40B4-20F-1



Switch-disconnector, 4 pole, 2000A, without protection, IEC, Fixed



INX40B4-20F-1 184076





# **Delivery program**

Product range			Air circuit-breakers/switch-disconnectors
Product range			Open switch-disconnectors
Current Range			Up to 4000 A
Protective function			without protection
Installation type			Fixed
Construction size			INX40
Release system			without releases
Standard/Approval			IEC
Number of poles			4 pole
Degree of Protection			IP31 with door seals, IP55 with protective cover
			optionally fittable by user with comprehensive accessories
Rated current = rated uninterrupted current	$I_n = I_u$	А	2000
Rated short-circuit making capacity up to 440V/690V 42/42	I <sub>cm</sub>	kA	145
Rated short-time withstand current t =1 s	I <sub>cw</sub>	kA	66
Rated short-time withstand current t =3 s	l <sub>cw</sub>	kA	53

# **Technical data**

General			
Standards			IEC/EN 60947
Ambient temperature			
Storage	θ	°C	-40 - +70
Ambient temperature		°C	-25 - +70
Mounting position			30° 30° 30° 30°
Utilization category			В
Degree of Protection			IP31 with door seals, IP55 with protective cover
Direction of incoming supply			as required
Main conducting paths			
Rated current = rated uninterrupted current	$I_n = I_u$	A	2000
Rated uninterrupted current at 50 °C	l <sub>u</sub>	А	2000
Rated uninterrupted current at 60 °C	lu	А	2000
Rated uninterrupted current at 70 °C	lu	А	2000
Rated impulse withstand voltage	U <sub>imp</sub>	V AC	12000
Rated operational voltage	Ue	V AC	690
Overvoltage category/pollution degree			111/3
Rated insulation voltage	Ui	V	1000
Switching capacity			
Rated short-circuit making capacity	l <sub>cm</sub>		
up to 440 V 50/60 Hz	I <sub>cm</sub>	kA	145
up to 690 V 50/60 Hz	I <sub>cm</sub>	kA	145
Operating times			
Closing delay via spring release		ms	30

	ms	35
	ms	40
	S	
Switching cycles (ON/ OFF)		10000
Switching cycles (ON/ OFF)		2000.
Switching cycles (ON/ OFF)		8000
Switching cycles (ON/ OFF)		16000.
	Ops./h	
Operations/h		60
	W	220
	kg	50
	mm	2 x 80 x 10
		These are values used in separate switchgear. The actual values will depend on the temperature around the circuit-breaker, which is influenced by the ambient temperature, the degree of protection (IP), the mounting height, the partitions, and any external ventilation. Depending on the specific switchgear design, this may result in derating, which can then be compensated for by increasing the cross- sectional area. Temperature rise tests in the specific switchgear can provide specific and detailed information.
	cycles (ON/ OFF) Switching cycles (ON/ OFF) Switching cycles (ON/ OFF) Switching cycles (ON/ OFF)	Switching cycles (0N/ OFF)Switching cycles (0N/ OFF)Switching cycles (0N/ OFF)Switching cycles (0N/ OFF)Operations/hOperations/hImage: Comparison of the sector of the s

### Design verification as per IEC/EN 61439

Design vernication as per icc/civ 01455			
Technical data for design verification			
Rated operational current for specified heat dissipation	In	А	2000
Equipment heat dissipation, current-dependent	P <sub>vid</sub>	W	220
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.

10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

#### **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Switch disconnector (EC000216)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Switch disconnector (ecl@ss10.0.1-27-37-14-03 [AKF060013])

ion as main switch ion as maintenance-/service switch ion as safety switch ion as safety switch ion as emergency stop installation ion as emergency stop installation ion as reversing switch ion as reversing switch ion as reversing switch ion as reversing switch is a rated operation voltage Ue AC V id operating voltage (Ue AC) V id operatin	Yes No No No 690 690 690 690 690 690 0	
ion as safety switch ion as emergency stop installation ion as reversing switch aber of switches . rated operation voltage Ue AC doperating voltage doperating voltage dopermanent current lu dopermanent current at AC-23, 400 V doperation power at AC-3, 400 V doperation power at AC-23, 400 V	No No No 690 690 - 690 2000	
ion as emergency stop installation ion as reversing switch is inclusted as the of switches is inclusted as the operation voltage Ue AC is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the operation power at AC-23, 400 V is inclusted as the ope	No No 690 690 - 690 2000	
ion as reversing switch ber of switches . rated operation voltage Ue AC d operating voltage d operating voltage d permanent current lu d permanent current at AC-23, 400 V d operation power at AC-3, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d operation power at AC-23, 400 V d short-time withstand current lcw d short-time short	No 690 690 - 690 2000	
Abber of switchesImage: Constraint of switches. rated operation voltage Ue ACV. rated operating voltageV. rated operating voltageV. rated operating voltageA. d permanent current luA. d permanent current at AC-23, 400 VA. d operation power at AC-3, 400 VKW. d operation power at AC-33, 400 VKA. d operation power at AC-23, 400 VKA	690 690 - 690 2000	
rated operation voltage Ue AC V d operating voltage V V d operating voltage AC V d permanent current Iu AC-23, 400 V d permanent current at AC-21, 400 V d operation power at AC-3, 400 V d short-time withstand current Icw AC AC KW d operation power at AC-23, 400 V	690 - 690 2000	
d operating voltageVd permanent current luAd permanent current at AC-23, 400 VAd permanent current at AC-21, 400 VAd operation power at AC-3, 400 VKWd short-time withstand current lcwKAd operation power at AC-23, 400 VKW	690 - 690 2000	
d permanent current luAd permanent current at AC-23, 400 VAd permanent current at AC-21, 400 VAd operation power at AC-3, 400 VKWd short-time withstand current lcwKAd operation power at AC-23, 400 VKA	2000	
d permanent current at AC-23, 400 VAd permanent current at AC-21, 400 VAd operation power at AC-3, 400 VKWd operation power at AC-3, 400 VKAd operation power at AC-23, 400 VKA		
ad permanent current at AC-21, 400 V     A       ad operation power at AC-3, 400 V     kW       ad short-time withstand current Icw     kA       ad operation power at AC-23, 400 V     kW	0	
d operation power at AC-3, 400 V kW d short-time withstand current Icw kA d operation power at AC-23, 400 V kW	0	
d short-time withstand current Icw kA d operation power at AC-23, 400 V kW		
d operation power at AC-23, 400 V kW	0	
	66	
ching power at 400 V kW	0	
	0	
litioned rated short-circuit current Iq kA	144	
ber of poles	4	
ber of auxiliary contacts as normally closed contact	0	
ber of auxiliary contacts as normally open contact	0	
ber of auxiliary contacts as change-over contact	2	
or drive optional	Yes	
or drive integrated	No	
age release optional	Yes	
ce construction	Built-in device fixed built-in technique	9
able for ground mounting	Yes	
able for front mounting 4-hole	No	
able for front mounting centre	No	
able for distribution board installation	Yes	
able for intermediate mounting	No	
ur control element	Green	
of control element	Push button	
lockable	Yes	
of electrical connection of main circuit		
ree of protection (IP), front side	Rail connection	
ree of protection (NEMA)	Rail connection	



