

## **SMALL COMPACT THERMOSTAT**

## KTO 111 / KTS 111



> Push-In terminals for tool-free connection

**TECHNICAL DATA** 

- > for use in up to 5,000 m altitude
- > Easy adjustability of switch temperature setting
- > Improved air intakes for ventilation

The mechanical thermostats KTO 111 and KTS 111 are two state regulators for use up to 5,000 meters in altitude, thanks to optimised air gap and increased creepage distance. The conductor can easily be connected via Push-In clamps without tools.


**KTO 111:** Thermostat (NC); contact breaker for regulating heaters. The contact opens when temperature is rising.


KTS 111: Thermostat (NO); contact maker for regulating of filter fans and heat exchangers or for switching signal devises when temperature limit has been exceeded. The contact closes when temperature is rising.















## Connection diagrams



Filter fan, Cooling equipment, Signal device




connection

## Switch temperature difference 7 K (±4 K tolerance) Sensor element thermostatic bimetal Contact type snap-action contact Service life up to 100,000 cycles Max. operating voltage, frequency range AC 250 V, 50-60 Hz Max. inrush current AC 16 A for 10 sec. Connection<sup>1</sup> 2 Push-In clamps rigid wire 2.5 mm<sup>2</sup> (AWG 14) stranded wire1 1.5 mm2 (AWG 16) Mounting clip for 35 mm DIN rail, EN 60715 Casing plastic according to UL94 V-O, light grey Dimensions 60 x 33 x 41 mm Weight approx. 40 g Fitting position variable -20 to +80 °C (-4 to +176 °F) / -45 to +80 °C (-49 to +176 °F) Operating/Storage temperature Operating/Storage humidity max. 90 % RH (non-condensing) Protection type/Protection class IP20 / II Overvoltage category/Altitude II: up to 5,000 m; III: up to 2,000 m

1 Stripped length of rigid wire: 10 to 12 mm. When connecting with wires, wire end ferrules must be used (square or trapezoid crimp). Length of wire end ferrule: 10 mm or 12 mm.

Important note: The contact system of the regulator is subjected to environmental influences, thus the contact resistance may change. This can lead to a voltage drop and/or self-heating of the contacts.



Setting range	Art. No. Contact breaker (NC)	Art. No. Contact maker (NO)	Switching capacity max.		Approvals	
0 to +60 °C	11100.0-00	11101.0-00	10 (2) A	VDE	UL in Progress	EAC
-10 to +50 °C	11100.0-01	11101.0-01	10 (2) A	VDE	UL in Progress	EAC
+20 to +80 °C	11100.0-02	11101.0-02	3 (2) A	VDE	UL in Progress	EAC
+32 to +140 °F	11100.9-00	11101.9-00	10 (2) A	VDE	UL in Progress	EAC
+14 to +122 °F	11100.9-01	11101.9-01	10 (2) A	VDE	UL in Progress	EAC